



# AJAX MultiTransmitter

MultiTransmitter is an integration module with 18 wired zones for connecting third-party detectors to Ajax security system. The module runs on 110–255 V AC or 12 V DC. Additionally, it can supply 12 V power to the connected detectors.

-  Replaces wired control panels
-  Simplifies the process of integrating wired security systems into Ajax by automatically merging information about the EOL resistors
-  Converts signals from wired detectors and sends alarms to the hub via Jeweller radio protocol

## Integrate multiple wired detectors at once

	MultiTransmitter	Transmitter
Alarm / tamper input	18 alarm and/or tamper inputs	1 tamper, 1 alarm input
Power supply output	12 V DC	3.3 V DC
Power supply	110-255 V AC, 50/60 Hz 12 V DC	3x CR123A batteries, 3 V
Detector/contact types	NO, NC (no R) EOL (NC with R) EOL (NO with R)	NO, NC

## Tech Specs

- Compatibility: All hubs and ReX
- Terminals:  
Power supply (+/-), alarm, tamper
- Detector contact types:  
NO, NC (no R)  
EOL (NC with R)  
EOL (NO with R)
- Number of alarm/tamper areas: 18
- Power supply: 110-255 V AC 50 / 60 Hz  
Backup: 12 V DC (battery not included)
- Power supply output: 12 V DC  
up to 1 A
- Jeweller radio technology:  
868.0–868.6 MHz  
depends on region
- Anti-sabotage:  
Device forgery prevention  
Jamming detection  
Anti-tamper
- Dimensions: 196 × 238 × 100 mm
- Weight: 805 g



MultiTransmitter comes in a protective container with a dedicated space for a rechargeable battery.